

# The quiet achiever.

Compact, efficient and highly economincal, the FS-1061DN is the ideal printer for small and home offices. This quiet black and white provides users with up to 25 pages per minute, paper saving duplex printing and connects easily to any PC with a standard USB interface.



# **Specifications**

### ECOSYS

ECOSYS stands for ECOlogy, ECOnomy and SYStem-printing. With long-life components, ECOSYS devices are designed to maximise durability and minimise the total cost of ownership with regard to maintenance, administration and consumables. The cartridge-free system means that only the toner has to be replaced regularly, and the drum units every 100,000 pages. The modular design concept allows you to add workflow-enhancing functions as required. Integrated system software provides long-term cross-network compatibility. Kyocera's long-life components cost you and the environment less.

### PRESCRIBE IIc

With the Kyocera page design and control language PRESCRIBE IIc, even complex graphics, logos and forms (multipart forms) can be created independently on the system and saved and updated in the printer. Consequently, integration into print files no longer applies. They are only accessed as required and therefore relieve the load on the network.

### GENERAL

Technology: Kyocera ECOSYS Laser Pages Per Minute: Up to 25 A4 pages per minute Warm-up time: 16 seconds or less Time to first print: 8.5 seconds or less Resolution: 1,200 dpi Memory: Standard 32MB Dimensions (W x D x H) / Weight: 358 x 276 x 241 mm / 6.7kg Power Consumption: Print: 346w Sleep mode: 3w Maximum Monthly Duty Cycle: 15,000 Pages Per Month

### PAPER HANDLING

Standard Paper Sources: 250 Sheet Drawer, 1 Sheet Manual Feed Tray Standard / Maximum Paper Sources: Two including Manual Feed Tray Standard Paper Drawer Size / Weight: Letter, Legal, A4, A5, B5, A6R, Custom/ 60 - 220 g/m2 Standard Duplex Paper Size / Weight: Letter, Legal, A4, A5 / 60 - 120 g/m2 Standard / Maximum Paper Capacity: 251 Sheets Multi-Purpose Tray Paper Size / Weight: Letter, Legal, A4, A5, B5, A6R, Custom/ 60 - 220 g/m2 Output Capacity: 150 Sheets Duplex Printing: Standard Duplex A4

# CONTROLLER

CPU / MHz: 390MHz PDL / Emulations: Host-based (GDI) Supported Client Operating Systems: Certified for Microsoft® Windows Vista® 32/64-bit, Windows XP® 32/62-bit, Windows Server 2003 32/64-bit, Windows Server 2008 32/64-bit, Windows 8, Mac OS X v10.5 Supported Network Operating Systems: Microsoft Windows, Server 2003, Windows Server 2008, XP, Vista, 2003 64-bit, XP 64-bit, (for Microsoft IPv6 compatible with Windows 2003, XP, and Vista); Mac OS X v10.5 Connectivity / Interfaces: Standard 10/100BASE-TX, High Speed USB 2.0 Network Protocols: Host, IP address, DNS server, WINS server Drivers: GX Driver, Status Monitor, PPD for Mac, PPD for Linux/UNIX Additional Print Features: LED Operation Panel, N-Up Printing Multi Language Support: English, French, Spanish

### CONSUMABLES TK-1129 Toner Kit

Micro-fine toner for 2,100 pages A4, at 5% coverage, in accordance with ISO19752 Capacity of starter toner is 1,000 pages A4, at 5% coverage, in accordance with ISO/IEC 19752 Maintenance Kit MK-1110: Installed every 100,000 pages

The FS-1061DN is robust and reliable. With Kyocera's proven ECOSYS long-life technology, it is a hassle-free printer you can depend on.





digital document solutions

Phone: 08 9328 4600 Email: dds@multifaxdds.com.au Web: www.multifaxdds.com.au



Kyocera Document Solutions does not warrant that any specifications mentioned will be error-free. Specifications are subject to change without notice. Information is correct at time of going to press. All other brand and product names may be registered trademarks or trademarks of their respective holders and are hereby acknowledged. KYOCERA Document Solutions Australia Pty. Ltd ABN 77 003 852 444

### The KYOCERA NetViewer

The KYOCERA NetViewer enables complete monitoring and control of all ECOSYS printers and digital Kyocera multifunction units from any Windows© PC and thus provides ideal network administration. It also supports the standardised SNMP protocol.

## Status Monitor and Command Centre

The Status Monitor shows the current printers condition and gives direct access to the Command Centre for the modification of settings that are not contained in the drivers (e.g. network settings, adjustment of sleep mode or blocking of the control panel).